WIDEBAND TAPE WHIP VHF-LOW ANTENNA



SKU#ANT-VL-TW

AB2267




The ANT-VL-TW antenna is expertly designed for use with manpack and handheld radios, operating within a frequency range of 30 to 108 MHz.

This VHF-L whip antenna is engineered for reliable performance across a variety of operational conditions, whether the radio is carried on the back, worn on the chest, or positioned on the ground. With no need for additional tuning, it ensures seamless and hassle-free operation.

The antenna features a radiating element crafted from durable multilayer steel tape material, offering exceptional flexibility and toughness. It also includes a specialized passive transformer tuning network, securely housed in a robust fiberglass casing located above the input coaxial connector.

Frequency	30 - 108Mhz
Impedance	50 Ohm
VSWR	< 4.5
Gain	Diagnal. 2
Polarization	Vertical
Max. power	20W
Connector type	modif. BNC/TNC
Height	1650mm
Mass	450g
Temperature range	-20 to +70 °C





110